

SVL230AW2

Multitone voice sounder | radio | orange LED beacon | 230V AC | white



Specifications

| | | | |
|--------------------|---|---------------------------------|---|
| Brand | SmartVOX® | Mounting type | Outside mounting lugs |
| CE certificate | Yes | Number of LEDs | 18 |
| Cable entry | -40°C to +60°C | Number of personalized messages | 128, 100% customisable |
| Colour | RAL 9003 white | Number of tones | 45 |
| Colour lens | Amber | Operating temperature | -25°C to +55°C |
| Communication | Radio LoRa | Operating voltage | 100-240V AC |
| Dimensions | 190mm x 275mm x 191,5mm | Rated current | 0,9A @ 230V AC |
| Good to know | Battery, cable glands, ventilation plug and counter nuts included | Relative humidity | Less than 90% (no condensation) at 20°C |
| Ingress protection | IP66 | Sound level (max.) | 126dB(A) @ 1m |
| LED life | >60 000h | Type | Combination modules light & sound |
| Light patterns | Steady, blinking and flash | Volume control | Full range control |
| Light source | LED | Weight | 2900g |
| Luminous intensity | 120cd | Window type | Fresnel |
| Material | ABS, self-extinguishing | | |

Good to know

This sounder has a built-in backup battery that can keep the system active for 6 hours.

